

Schauer® Battery Chargers

Schauer is a trademark of the Brookwood Group Inc.



Schauer
3210 Wasson Road
Cincinnati, Ohio 45209

1-800-899-VOLT
Fax: 1-513-791-7192
www.battery-chargers.com

MODEL JAC0336MAN, JAC0348MAN

**Fully Automatic
36 or 48 volt
Battery Maintainer**



Model JAC0336MAN Shown

- Extend the life of your batteries with this battery maintainer. Prevents battery sulfation during equipment storage.
- Maintainer for 36-volt or 48-volt battery systems. Use on 10 to 300-amp hour lead acid batteries, typical of golf carts, industrial scrubbers, etc.
- Current limiting.
- Fully automatic maintainer can be left on the battery in maintaining/float mode.
- Red LED indicates AC power on.
- Can be used for any type lead acid battery, including conventional, maintenance free, deep cycle, gelled-type, valve regulated batteries.
- Reverse polarity and short circuit proof.
- AC cordset length, 6 feet. DC cordset length, 4 feet with battery clips.
- Aluminum case.
- AC Input 100-240 volts, 50 or 60Hz Input voltage autosensed.

JAC0336MAN	2.5 AMPS	36 VOLTS	6.5" w x 3.5" h x 1.8" d	1.8 lbs.
JAC0348MAN	2.5 AMPS	48 VOLTS	6.5" w x 3.5" h x 1.8" d	1.8 lbs.